

## PP-7600 Jumper Setting

### ● SOFTWARE SWITCH 1

There is no hardware Dip Switch for PP7600 Series.

SWITCH 1		FUNCTION
1	2	Baud Rate
OFF	OFF	115200
OFF	ON	19200
ON	OFF	9600
ON	ON	38400
3		Interface select
OFF		DEFAULT / daughter board
ON		Onboard
4		Onboard Interface
OFF		USB
ON		Serial
5		USB Class
OFF		Printer Class
ON		CDC
6		printable width
OFF		512dots
ON		576dots
7		Paper width
OFF		80mm
ON		58mm
8		Auto cutter
OFF		Enable
ON		Disable

● SOFTWARE SWITCH 2 :

SWITCH 2	FUNCTION
<b>1</b>	<b>Paper Feed Back</b>
<b>OFF</b>	<b>Disable</b>
ON	Enable
<b>2</b>	<b>Cut Paper after Cover Return</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>3</b>	<b>Full Cut Paper</b>
<b>OFF</b>	<b>Disable</b>
ON	Enable
<b>4</b>	<b>Before Cut Paper</b>
<b>OFF</b>	<b>Normal Cut</b>
ON	Cut and without paper feed
<b>5</b>	<b>Busy condition</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>6</b>	<b>&lt; CR &gt; Auto Line Feed</b>
<b>OFF</b>	<b>Disable</b>
ON	Enable
<b>7</b>	<b>Parity Check</b>
<b>OFF</b>	<b>NONE</b>
ON	EVEN
<b>8</b>	<b>Handshaking</b>
<b>OFF</b>	<b>DTR/DSR</b>
ON	XON/XOFF

● SOFTWARE SWITCH 3 :

SWITCH 3				FUNCTION
1				Raster Bitmap Printing
OFF				Batch Print
ON				Line Print
2				Print Speed
OFF				170mm/s
ON				200mm/s
3				Thai Font mode
OFF				1 PASS
ON				3 PASS
4				UPOS Write
OFF				Disable
ON				Enable
5	6	7	8	Print Density
OFF	OFF	OFF	OFF	100%
ON	OFF	OFF	OFF	105%
OFF	ON	OFF	OFF	110%
ON	ON	OFF	OFF	115%
OFF	OFF	ON	OFF	120%
ON	OFF	ON	OFF	125%
OFF	ON	ON	OFF	130%
ON	ON	ON	OFF	95%
OFF	OFF	OFF	ON	90%
ON	OFF	OFF	ON	85%
OFF	ON	OFF	ON	80%

● **SOFTWARE SWITCH 4 :**

SWITCH 4		FUNCTION
1		Beep Sound after Cut paper
OFF		Disable
ON		Enable
2	3	Barcode Height Reduction
OFF	OFF	Disable
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
4	5	Line Space Reduction
OFF	OFF	Disable
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
6	7	Line Feed Reduction
OFF	OFF	Disable
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
8		Switch 1 Selection
OFF		Zero packet
ON		NAK packet

※ J6: Use for Firmware download.

J6	FUNCTION
Open	Normal Mode
Short	Firmware download mode