

GB-1000M JUMPER SETTING

- **JP1 : CMOS Select**

Pin 1-2 Short : Normal

Pin 2-3 Short : Clear CMOS

- **JP2 : COM2 5V/12V DC SUPPLY SELECT**

Pin 1-3 Short : COM2 Pin9 connected to 5V

Pin 3-5 Short : COM2 Pin9 connected to RI

Pin 2-4 Short : COM2 Pin1 connected to 12V

Pin 4-6 Short : COM2 Pin1 connected to DCD

- **JP3 : COM1 5V/12V DC SUPPLY SELECT**

Pin 1-3 Short : COM1 Pin9 connected to 5V

Pin 3-5 Short : COM1 Pin9 connected to RI

Pin 2-4 Short : COM1 Pin1 connected to 12V

Pin 4-6 Short : COM1 Pin1 connected to DCD

- **JP4 : COM3 5V/12V DC SUPPLY SELECT**

Pin 1-3 Short : COM3 Pin9 connected to 5V

Pin 3-5 Short : COM3 Pin9 connected to RI

Pin 2-4 Short : COM3 Pin1 connected to 12V

Pin 4-6 Short : COM3 Pin1 connected to DCD

- **JP5 : COM4 5V/12V DC SUPPLY SELECT**

Pin 1-3 Short : COM4 Pin9 connected to 5V

Pin 3-5 Short : COM4 Pin9 connected to RI

Pin 2-4 Short : COM4 Pin1 connected to 12V

Pin 4-6 Short : COM4 Pin1 connected to DCD

- **JP6 : VGA2 12V DC SUPPLY SELECT FOR CRT**

Open VGA DSUB Pin 9 =Not Connect

Close : VGA DSUB Pin 9 =12V

